# G3VM-353B/E MOS FET Relays

### DIP 6-pin package, Analog-switching MOS FET Relays with SPST-NC Contact.

**RoHS compliant** 



- Communication equipment
- Security systems
- FA systems
- Test & Measurement equipment





Note: The actual product is marked differently from the image shown here.

mRON 040

### List of Models

Package type	Contact form	Terminals	Load voltage	Model	Minimum package quantity	
	Contact Ionni		(peak value) *	Model	Number per tube	Number per tape and reel
DIP6	41-	PCB Terminals		G3VM-353B	50	-
	(SPST-NC)	Surface-mounting Terminals	350 V	G3VM-353E	50	
	(3F31-100)			G3VM-353E (TR)	-	1,500

\* The AC peak and DC value are given for the load voltage.

### ■ Absolute Maximum Ratings (Ta = 25°C)

Item			Symbol	Rating	Unit	Measurement conditions		
	LED forward current		lF	50	mA			
Input	Repetitive peak LED forward current		IFP	1	А	100 µs pulses, 100 pps		
	LED forward current reduction rate		∆IF/°C	-0.5	mA/°C	Ta ≥ 25°C		
	LED reverse voltage		VR	5	V			
	Connection temperature		TJ	125	°C			
Output	Load voltage (AC peak/DC)		Voff	350	V			
	Continuous load current	Connection A	lo	150	mA	Connection A: AC neck/DC		
		Connection B		150		Connection A: AC peak/DC Connection B and C: DC		
		Connection C		300		Connection D and C. DC		
	ON current Connection A			-1.5				
	reduction	Connection B	∆lo/°C	-1.5	mA/°C	Ta ≥ 25°C		
	rate	Connection C		-3.0				
	Connection temperature		TJ	125	°C			
Dielectric strength between I/O (See note 1.)			VI-0	2500	Vrms	AC for 1 min		
Ambient operating temperature			Та	-40 to +85	°C	With no icing or condensation		
Ambient storage temperature			Tstg	-55 to +125	°C	With no icing or condensation		
Soldering temperature			-	260	°C	10 s		

Note: 1. The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side. **Connection Diagram** 



### Electrical Characteristics (Ta = 25°C)

Item		Symbol	Minimum	Typical	Maximum	Unit	Measurement conditions	1	
LED forward voltage Reverse current Capacity between terminals		VF	1.0	1.15	1.3	V	IF = 10 mA		
		IR	-	-	10	μA	VR = 5 V		
dul	Capacity between terminals		Ст	-	30	-	pF	V = 0, f = 1 MHz	Note:
	Trigger LED forwa	ger LED forward current		-	1	3	mA	IOFF = 10 μA	
Output	Maximum	Connection A		-	15	25	Ω	lo = 150 mA	
	resistance with	Connection B	Ron	-	8	14	Ω	lo = 150 mA	
	output ON	ON Connection C		-	4	7	Ω	lo = 300 mA	
	Current leakage when the relay is open		ILEAK	-	-	1.0	μA	IF = 5 mA, VOFF = 350 V	
	Capacity between terminals		COFF	-	85	-	pF	V = 0, f = 1 MHz, I⊧ = 5 mA	
Capacity between I/O terminals		CI-0	-	0.8	-	pF	f = 1 MHz, Vs = 0 V		
Insulation resistance between I/O terminals			Ri-o	1000	-	-	MΩ	VI-0 = 500 VDC, $RoH \le 60\%$	
Turn-ON time		ton	-	0.1	1.0	ms	$I_F = 5 \text{ mA}, \text{ RL} = 200 \Omega,$		
Turn-OFF time			toff	-	1.0	3.0	ms	VDD = 20 V(See note 2.)	

Note: 2. Turn-ON and Turn-OFF Times



71

# G3VM-353B/E

### Recommended Operating Conditions

Use the G3VM under the following conditions so that the Relay will operate properly.

Item	Symbol	Minimum	Typical	Maximum	Unit
Load voltage (AC peak/DC)	Vdd	-	-	280	V
Operating LED forward current	lF	5	-	25	mA
Continuous load current (AC peak/DC)	lo	-	-	150	mA
Ambient operating temperature	Та	-20	-	65	°C

### Engineering Data

# LED forward current vs. Ambient temperature



Continuous load current vs. On-state voltage



Turn ON, Turn OFF time vs. LED forward current



## Continuous load current vs. Ambient temperature



**On-state resistance vs. Ambient** 

Ron - Ta

temperature

l<sub>O</sub> = 150 mA t < 1 s

20

15

10

5

0

-20

0

20

On-state resistance Rov (Ω)

LED forward current vs. LED forward voltage



#### Trigger LED forward current vs. Ambient temperature



Turn ON, Turn OFF time vs. Ambient temperature

40

60

Ambient temperature Ta (°C)

80

100



# Current leakage vs. Ambient temperature



### ■ Safety Precautions

• Refer to "Common Precautions" for all G3VM models.

#### ■ Appearance

#### DIP (Dual Inline Package)



Note: The actual product is marked differently from the image shown here.

### Dimensions

(Unit: mm)



Application examples provided in this document are for reference only. In actual applications, confirm equipment functions and safety before using the product.
Consult your OMRON representative before using the product under conditions which are not described in the manual or applying the product to nuclear control systems, railroad systems, aviation systems, vehicles, combustion systems, medical equipment, amusement machines, safety equipment, and other systems or equipment that may have a serious influence on lives and property if used improperly. Make sure that the ratings and performance characteristics of the product provide a margin of safety for the system or equipment, and be sure to provide the system or equipment with double safety mechanisms.

Note: Do not use this document to operate the Unit.

#### OMRON Corporation ELECTRONIC AND MECHANICAL COMPONENTS COMPANY Contact:

Contact: www.omron.com/ecb

Cat. No. K249-E1-01 0413(0413)(O)