

HCPT1309 Series **Power Inductors**



Description

- 105°C maximum total temperature operation
- 13.2mm x 13.2mm x 9.0mm through hole package
- Core material: Powder Iron
- Inductance range from 0.20µH to 3.3µH
- Current range from 90.0 Amps to 11.4 Amps
- Frequency range up to 1MHz

Applications

- Next generation processors
- High current DC-DC converters
- VRM, multi-phase buck regulator
- Desktop computers
- Video game power

Environmental Data

- Storage temperature range: -40°C to +105°C
- Operating temperature range: -40°C to +105°C (range is application specific)
- Solder reflow temperature: +260°C max. for 10 seconds maximum



Packaging

Supplied in bulk packaging, 100 parts per tray

Part Number	OCL (1) nominal +/- 20% (μΗ)	Irms (2) Amperes	Isat Amperes (3) Peak 20% rolloff @20°C	Isat Amperes (4) Peak 30% rolloff @20°C	DCR (mΩ) nom @20°C	K-factor (5)
HCPT1309-R20-R	0.20	43.1	72.2	90.0	0.426	154.1
HCPT1309-R47-R	0.49	34.0	43.3	55.0	0.624	92.4
HCPT1309-1R0-R	0.96	19.4	30.9	40.0	1.90	66.0
HCPT1309-1R5-R	1.59	13.7	24.1	30.6	3.82	51.4
HCPT1309-2R2-R	2.27	12.5	19.7	25.0	4.10	42.0
HCPT1309-3R3-R	3.31	11.4	16.7	21.0	4.80	35.6

 OCL: Open Circuit Inductance test parameters: 100kHz, 0.1Vrms, 0.0Adc.
 Irms: DC current for an approximate ∆T of 40°C without core loss. Derating is necessary for AC currents. PCB layout, trace thickness and width, air-flow, and proximity of other heat generating components will affect the temporature rise. It is recommended that the temperature of the part not exceed 105°C under worst case operating conditions verified in the end application.

(3) Isat Amperes peak for approximately 20% rolloff (@20°C)

(a) Isat Amperes peak for approximately 20% rolloff (@20°C)
(b) K-factor: Used to determine B p-p for core loss (see graph).
B p-p = K*L*∆I, B p-p: (Gauss), K: (K factor from table), L: (Inductance in uH), ∆I (Peak to peak ripple current in Amps).

Mechanical Diagrams



Dimensions are in millimeters. wwllyy = Date Code. R = Revision Level.

COOPER Bussmann

COILTRONICS[®] **HCPT1309** Series

Power Inductors

Core Loss



Inductance Characteristics



COOPER Bussmann

PM-4138 3/07

Visit us on the Web at www.cooperbussmann.com © Cooper Electronic

1225 Broken Sound Pkwy. Suite F Boca Raton, FL 33487 Technologies 2007 Tel: +1-561-998-4100 Toll Free: +1-888-414-2645 Fax: +1-561-241-6640

> This bulletin is intended to present product design solutions and technical information that will help the end user with design applications. Cooper Electronic Technologies reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Cooper Electronic Technologies also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

Life Support Policy: Cooper Electronic Technologies does not authorize the use of any of its products for use in life support devices or systems without the express written approval of an officer of the Company. Life support systems are devices which support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.