MALLORY Mallory	y Sonale	rt Products,	Inc.	Part #:	JT028-R-CSL	
Sales Outline Drawing				Revision:	В	
Specifications:						
Stack Number:	1					
LED Color:	RED					
Connection Wires:	Red and Brown					
LED Current Draw:	<50mA			<u> </u>		
Rated Voltage:	COULT		24 VAC/DC			
Operating Voltage:			20-28 VAC/DC			
Sound Level Category:	Loud	Loud	Loud	,	Loud	
Sound Level Category.	Loud	Loud	Loud		Continuous for 5 sec then 0.1s	
Mada of Onematica	0	Madisus Dulas (FDDC)	Davida Dulas //	,		
Mode of Operation:	Continuous	Medium Pulse (5PPS)	Double Pulse (0.5PPS)		beep until reset	
	Black and Gray	Black and Gray Wires;	Black and Gray Wires; Purple wire connected to		Black and Gray wires; Orange and	
Connection:	Wires	Orange wire connected			Purple wires connected to	
	********	to Green/Yellow wire	Green/Yellow wire		Green/Yellow wire	
Sound Current Draw:	40mA Max.	40mA Max.	40mA Ma	IX.	40mA Max.	
Loudness @ 1m:			80-85 dB(A) Ty	35 dB(A) Typ.		
Frequency:		2000 ± 500 Hz				
Total Max Current:	<90mA with all LED's and Sound unit working					
Operating Temperature:	-25° ~ +60°C					
Lens Color:	Opaque White					
Material:	ABS FR15U					
Mounting Method:	Stainless Steel Pole					
Weight Typical (g):			640			
NEMA 12:	Approved					
Options:	Please contact factory.					
		—16.6 [422.0]————		GA [Ø5.2] aces	Ø0.57 [Ø14.6] for wires	
2.4 [61 2.7 [68.3] TOP VIEW	.83		5crews for mounting 7.39 [9.9]	\rightarrow		
LED OPERATION: CONN	ECT STACK COL	OR WIRE TO POWER A	ND BROWN WIRE	TO POW	ĒR.	
SOUND OPERATION: CONNECT GRAY AND BLACK WIRES TO POWER FOR CONTINUOUS SOUND.						
	FOR MEDIUM PULSE, CONNECT GRAY & BLACK TO POWER AND ORANGE WIRE TO					
GREEN/YELLOW WIRE. FOR DOUBLE PULSE, CONNECT GRAY & BLACK TO POWER AND PURPLE WIRE TO						
	GREEN/YELLOW WIRE. FOR CONT/BEEP, CONNECT GRAY & BLACK TO POWER AND ORANGE & PURPLE TO					
	GREEN/YELLOV	•	LACK TO FOWER	AND UKA	INOL & FUNFEL TO	