


MAXIM**Low-Voltage Reference****MAX8069****General Description**


The MAX8069 is a 1.2V temperature-compensated voltage reference. It uses the bandgap principle to achieve excellent stability and low noise at reverse currents down to 60µA. The MAX8069 also features excellent stability, freedom from oscillation. The MAX8069 is a functional alternative to Maxim's ICL8069 with an identical pinout.

Applications

- Analog-to-Digital Converters
- Digital-to-Analog Converters
- Threshold Detectors
- Voltage Regulators
- Portable Instruments

Typical Operating Circuit

(a) Simple Reference (1.2V or Less)



(b) Double-Regulated 100mV Reference for ICL7107 One-Chip DPM Circuit

Features

- ◆ Temperature Coefficient Guaranteed to 25ppm/°C (max)
- ◆ Low Bias Current: 60µA (min)
- ◆ Low Dynamic Impedance
- ◆ Low Reverse Voltage
- ◆ Low Cost

Ordering Information

| PART | TEMP RANGE | PIN-PACKAGE | PKG CODE |
|-------------|----------------|-------------|----------|
| MAX8069ESA+ | -40°C to +85°C | 8 SO | S8-2 |
| MAX8069CCZQ | 0°C to +70°C | TO-92 | C92-2 |


+Denotes lead-free package.

Selector Guide

| PART | TEMP RANGE | PIN-PACKAGE | MAX TEMP CO (ppm/°C) |
|-------------|----------------|-------------|----------------------|
| MAX8069ESA+ | -40°C to +85°C | 8 SO | 25 |
| MAX8069CCZQ | 0°C to +70°C | TO-92 | 50 |

Pin Configurations

TOP VIEW



Pin Configurations continued at end of data sheet.

MAXIM

Maxim Integrated Products 1

For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

Low-Voltage Reference

ABSOLUTE MAXIMUM RATINGS

| | |
|---------------------------------|--|
| Reverse Voltage | (Note 1) |
| Forward Current..... | 10mA |
| Reverse Current..... | 10mA |
| Power Dissipation..... | Limited by Max Forward/Reverse Current |
| Storage Temperature Range | -65°C to +150°C |

| | |
|---|----------------|
| Operating Temperature Range | |
| MAX8069CCZQ | 0°C to +70°C |
| MAX8069ESA | -40°C to +85°C |
| Lead Temperature (soldering, 10s) | +300°C |

Note 1: In normal use, the reverse voltage cannot exceed the reference voltage. However, when plugging units into a powered-up test fixture, an instantaneous voltage equal to the compliance of the test circuit will be seen. This should not exceed 20V.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(TA = +25°C, unless otherwise noted.) (Note 2)

| PARAMETER | CONDITIONS | | MIN | TYP | MAX | UNITS |
|--|---|-------------|------|------|------|----------|
| Output Voltage | $I_R = 500\mu A$ | | 1.20 | 1.22 | 1.25 | V |
| Output Voltage Temperature Coefficient | $I_R = 500\mu A$, TA = TMIN to TMAX | MAX8069ESA | | 25 | | ppm/°C |
| | | MAX8069CCZQ | | 50 | | |
| Output Voltage Change | $60\mu A \leq I_R \leq 5mA$ | | | 15 | 20 | mV |
| Reverse Dynamic Impedance | $I_R = 60\mu A$ | | | 1 | 2 | Ω |
| | | | | 0.6 | 2 | |
| Forward Voltage Drop | $I_R = 500\mu A$ | | | 0.6 | 1 | V |
| RMS Noise Voltage | 10Hz $\leq f \leq 10kHz$, $I_R = 500\mu A$ | | | 20 | | μV |
| Reverse Current Range | | | 0.06 | | 5.0 | mA |




Note 2: If circuit strays in excess of 200pF are anticipated, a 4.7μF shunt capacitor will ensure stability under all operating conditions.

Low-Voltage Reference


MAX8069

Typical Operating Characteristics

($T_A = +25^\circ\text{C}$, unless otherwise noted.)




Pin Configurations (continued)



Low-Voltage Reference

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to www.maxim-ic.com/packages.)



Revision History

Pages changed at Rev 1: 1, 2, 4.

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

4 **Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600**

© 2006 Maxim Integrated Products

MAXIM is a registered trademark of Maxim Integrated Products, Inc.