

### Features

- One upstream USB port terminator, EMI filter and transient overvoltage protector in a single surface-mount package
- Compact SC70 or SOT23 package saves board space and lowers manufacturing costs compared to discrete solutions
- ESD protection to ±30kV contact discharge per MIL-STD-883D, method 3015
- ESD protection to ±15kV contact discharge per IEC 61000-4-2 international standard
- Lead-free version available

### **Applications**

- ESD protection and termination of USB port
- All USB peripherals (PC printers, scanners, zip drives, etc.)
- PDAs / handheld PCs
- Digital cameras
- Wireless Handets
- MP3 Players
- Cable Modems

### **Product Description**

The PACUSB-U1, PACUSB-U2, and PACUSB-U3 are single-channel USB upstream-port termination networks.

The PACUSB-U1/U2/U3 integrate EMI/RFI filter components R1 and C1, as recommended by the USB specification. Because these are upstream USB devices, they are terminated with a single 1.5kW pull-up resistor to  $V_{3.3}$  (R2).

There are three options for the value of the series resistor R1:

- For PACUSB-U1, R1=15Ω
- For PACUSB-U2, R1=33 $\Omega$
- For PACUSB-U3, R1= $22\Omega$

This series resistance plus the USB driver output resistance must be close to the USB cable's characteristic impedance of  $45\Omega$  ( $90\Omega$  balanced) to minimize transmission line reflections.

In addition, these parts provide a very high level of protection for sensitive electronic components that may be subjected to electrostatic discharge (ESD). The input and output pins are designed and characterized to dissipate ESD strikes of  $\pm 15$ kV safely, a level well beyond the maximum requirements of the IEC 61000-4-2 international standard.

Using the MIL-STD-883D (Method 3015) specification for Human Body Model (HBM) ESD, all pins are protected for contact discharges to greater than ±30kV.

The PACUSB-U1/U2/U3 is housed in either a 6-pin SC70 or 6-pin SOT23 package and is available with optional lead-free finishing.

#### **Electrical Schematic**



#### i = input c = connector

#### PACKAGE / PINOUT DIAGRAMS



Note: Drawings are not to scale.

PIN DESCRIPTIONS					
PIN	NAME	DESCRIPTION			
1	D1_i	The USB Controller side of the D+ or D- bidirectional transmission line of the differential pair defined by USB standards.			
2	GND	The ground reference for the PACUSB-U1/U2/U3 device.			
3	D2_i	The USB Controller side of the D- or D+ bidirectional transmission line of the differential pair defined by USB standards.			
4	D2_c	The connector side of the D- or D+ bidirectional transmission line of the differential pair defined by USB standards.			
5	V <sub>3.3</sub>	The 3.3V supply voltage for the PACUSB-U1/U2/U3 device.			
6	D1_c	The connector side of the D+ or D- bidirectional transmission line of the differential pair defined by USB standards.			

## **Ordering Information**

PART NUMBERING INFORMATION						
			Standard Flnish		Lead-fre	e Finish
R1 Value (Ω)	Pins	Package	Ordering Part Number <sup>1</sup>	Part Marking	Ordering Part Number <sup>1</sup>	Part Marking
15	6	SC70-6	PACUSB-U1	UU1	PACUSB-U1R	U1R
15	6	SOT23-6	PACUSB-U1Y6	UU1Y	PACUSB-U1Y6R	U1YR
33	6	SC70-6	PACUSB-U2	UU2	PACUSB-U2R	U2R
33	6	SOT23-6	PACUSB-U2Y6	UU2Y	PACUSB-U2Y6R	U2YR
22	6	SC70-6	PACUSB-U3	UU3	PACUSB-U3R	U3R
22	6	SOT23-6	PACUSB-U3Y6	UU3Y	PACUSB-U3Y6R	U3YR

Note 1: Parts are shipped in Tape & Reel form unless otherwise specified.

## Specifications

ABSOLUTE MAXIMUM RATINGS				
PARAMETER	RATING	UNITS		
V <sub>3.3</sub> (Supply Voltage)	5.5	V		
Operating Temperature Range	-40 to +85	°C		
Storage Temperature Range	-65 to +150	°C		
DC Power to Resistor	100	mW		
Package Power	200	mW		

### STANDARD OPERATING CONDITIONS

PARAMETER	RATING	UNITS
V <sub>33</sub> (Supply Voltage)	3.3	V
Ambient Operating Temperature	-40 to +85	°C

	ELECTRICAL OPERATING CHARACTERISTICS						
SYMBOL	PARAMETER	CONDITIONS	MIN	ТҮР	МАХ	UNITS	
R1	Resistance R1 (PACUSB-U1 only)	Measured at $T_A = 25^{\circ}C$	12	15	18	Ω	
R1	Resistance R1 (PACUSB-U2 only)	Measured at $T_{A} = 25^{\circ}C$	26	33	40	Ω	
R1	Resistance R1 (PACUSB-U3 only)	Measured at $T_{A} = 25^{\circ}C$	18	22	26	Ω	
R2	Resistance R2	Measured at $T_A = 25^{\circ}C$	1.2	1.5	1.8	kΩ	
C1	Capacitance C1	Measured at 1 MHz, 2.5VDC, $T_A = 25^{\circ}C$	38	47	56	pF	
I <sub>leak</sub>	Diode Leakage Current to GND	At 3.3VDC and $T_A = 25^{\circ}C$		1	100	nA	
V <sub>D1</sub>	Diode Reverse-biased Stand-off Voltage	I = 10μΑ,Τ <sub>4</sub> = 25°C	5.5			V	
V <sub>D2</sub>	Signal Clamp Voltage Positive Clamp Negative Clamp	@ 10mA, T <sub>A</sub> = 25°C @ 10mA, T <sub>A</sub> = 25°C	5.6 -1.2	6.8 -0.8	8.0 -0.4	V V	
V <sub>ESD</sub>	In-system ESD Withstand Voltage						
	Human Body Model, MIL-STD- 883, Method 3015	Note 1	±30			kV	
	IEC 61000-4-2, contact discharge method (I/O pins)	Note 1	±15			kV	
	IEC 61000-4-2, contact discharge method (V <sub>3.3</sub> pin)	Note 1	±25			kV	
V <sub>CLAMP</sub>	Clamping Voltage during ESD Discharge Positive Negative	MIL-STD-883, Method 3015, 8kV; Note 1		10 -5		V V	

Note 1: ESD applied to input/output/V<sub>3.3</sub> pins with respect to GND, one at a time. Clamping voltage is measured at the opposite side of the EMI filter to the ESD pin (i.e., if ESD is applied to pin 1, then clamping voltage is measured at pin 6). Unused pins are open.

### **Application Information**

The PACUSB-U1/U2/U3 is targeted for upstream USB ports (peripherals). It provides series termination, EMI filtering, and ESD protection for the two USB data lines D+ and D-.

The USB Specification revision 1.1 provides for two data rates:

- The Full Speed signaling bit rate at 12 Mbits per second, and
- The Low Speed signaling bit rate at 1.5 Mbits per second.

The speed is selected by connecting one of the data lines (D+ or D-) to a 3.3V supply voltage via a  $1.5k\Omega$  pullup resistor (R2).

#### **Connections for Full Speed Operation**

Full Speed devices have the pull-up resistor (R2) connected to the D+ data line, as shown in Full Speed Connection. Pin1 is tied to the D+ line of the USB controller. Pin 6 is connected to the D+ line on the USB connector.

#### **Connections for Low Speed Operation**

Low Speed devices have the pull-up resistor (R2) connected to the D- data line, as shown in Low Speed Connection. Pin 1 is tied to the D- line of the USB controller; pin 6 is connected to the D- line on the USB connector.



Figure 1. Full Speed Connection



Figure 2. Low Speed Connection

### **Mechanical Details**

PACUSB-U1/U2/U3 devices are available in 6-pin SC70 and 6-pin SOT23 packages.

#### **SC70 Mechanical Specifications**

Dimensions for the PACUSB-U1/U2/U3 supplied in a SC70-6 package are presented below. For complete information on the SC70, see the California Micro Devices SC70 Package Information document.

PACKAGE DIMENSIONS					
Package	MO-203 Issue A				
Pins		6			
Dimensions	Millimeters				
Dimensions	Min	Max			
А	0.80	1.10			
A1	0.00	0.10			
A2	0.70	1.00			
В	0.15	0.30			
с	0.08	0.25			
D	1.85	2.25			
E	1.15	1.35			
е	0.65 BSC				
HE	2.00	2.40			
L	0.26	0.46			
# per tape and reel	3000 pcs				



Package Dimensions for SC70-6.

## **Mechanical Details (continued)**

#### **SOT23 Mechanical Specifications**

Dimensions for the PACUSB-U1/U2/U3 supplied in a SOT23-6 package are presented below. For complete information on the SOT23, see the California Micro Devices SOT23 Package Information document.

PACKAGE DIMENSIONS						
Package	MO-178					
Pins	6					
Dimensions	Millimeters		Inches			
Dimensions	Min	Max	Min	Max		
Α		1.45		0.057		
A1	0.00	0.15	0.000	0.006		
b	0.30	0.50	0.012	0.020		
с	0.08	0.22	0.003	0.009		
D	2.75	3.05	0.108	0.120		
E	2.60	3.00	0.102	0.118		
E1	1.45	1.75	0.057	0.069		
е	0.95	BSC	0.0374 BSC			
e1	1.90 BSC		0.0748 BSC			
L	0.60 REF 0.0236 REF			86 REF		
# per tape and reel	3000 pcs					
Controlling dimension: inches						



Package Dimensions for SOT23-6.

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other application in which the failure of the SCILLC product create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email I: orderlit@onsemi.com N. American Technical Support: 800-282-9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81-3-5773-3850 ON Semi conductor Websi te: www.onsemi.com

Order Li terature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative