

Pin Assignments

1IN+

1IN-

DTC

CT 5

RT 6

GND

C1

FEEDBACK [



2IN+

2IN-

C2

OUTPUT CTRL

14 REF

16

15

13

12 V_{CC}

11

10 E2

9 E1

VOLTAGE MODE DUAL OUTPUT PWM CONTROLLER

(Top View)

 \cap

2

3

4

7

8

Description

The AZ494 is a voltage mode pulse width modulation switching regulator control circuit designed primarily for power supply control.

The AZ494 consists of a reference voltage circuit, two error amplifiers, an on-chip adjustable oscillator, a dead-time control (DTC) comparator, a pulse-steering control flip-flop, and an output control circuit. The precision of voltage reference (V_{REF}) is improved up to $\pm 1\%$ through trimming and this provides a better output voltage regulation. The AZ494 provides for push-pull or single-ended output operation, which can be selected through the output control.

The difference between AZ494A and AZ494C is that they have 4.95V and 5V reference voltage respectively.

The AZ494 is available in standard packages of PDIP-16 and SO-16.

Features

- Stable 4.95V/5V Reference Voltage Trimmed to ±1.0% Accuracy
- Uncommitted Output TR for 200mA Sink or Source Current
- Single-End or Push-Pull Operation Selected by Output Control
- Internal Circuitry Prohibits Double Pulse at Either Output
- Complete PWM Control Circuit with Variable Duty Cycle
- On-Chip Oscillator with Master or Slave Operation
- Totally Lead-Free & Fully RoHS Compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)

Applications

- SMPS
- Back Light Inverter
- Charger

Notes:

1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS) & 2011/65/EU (RoHS 2) compliant.

- 2. See http://www.diodes.com/quality/lead_free.html for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.

(Top View)

SO-16







Output Function Control Table

| Signal for Output Control | Output Function |
|---------------------------|---------------------------------|
| V ₁ = GND | Single-ended or parallel output |
| VI = VREF | Normal push-pull operation |

Typical Applications Circuit



Pulse Width Modulated Step-Down Converter





Functional Block Diagram



Absolute Maximum Ratings (Note 4)

| Symbol | Parameter | Ra | ating | Unit | | |
|------------------|-------------------------------------------------|-------------------------------|-------|-------------------|--|---|
| V _{CC} | Supply Voltage (Note 5) | 40 | | V | | |
| VI | Amplifier Input Voltage | -0.3 to V _{CC} + 0.3 | | V | | |
| Vo | Collector Output Voltage | 40 | | V | | |
| lo | Collector Output Current | 250 | | mA | | |
| â | | M Package | 73 | ⁰ 0111 | | |
| ΑΙθ | Package Thermal Impedance (Note 6) | P Package | 67 | °C/W | | |
| _ | Lead Temperature 1.6mm from case for 10 seconds | +260 | | °C | | |
| T _{STG} | Storage Temperature Range | -65 to +150 | | °C | | |
| _ | ESD Rating (Machine Model) | 200 | | 200 | | V |

Notes: 4. Stresses greater than those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "Recommended Operating Conditions" is not implied. Exposure to "Absolute Maximum Ratings" for extended periods may affect device reliability.

5. All voltage values are with respect to the network ground terminal.

6. Maximum power dissipation is a function of $T_J(max)$, θ_{JA} and T_A . The maximum allowable power dissipation at any allowable ambient temperature is $P_D = (T_J(max) - T_A)/\theta_{JA}$. Operating at the absolute maximum T_J of +150°C can affect reliability.





Recommended Operating Conditions

| Symbol | Parameter | Min | Тур | Max | Unit |
|-----------------------------------|-------------------------------------------|---------|-------|---------------------|------|
| Vcc | Supply Voltage | 7 | 15 | 36 | V |
| V _{C1} , V _{C2} | Collector Output Voltage | - | 30 | 36 | V |
| I _{C1} , I _{C2} | Collector Output Current(Each Transistor) | - | - | 200 | mA |
| VI | Amplifier Input Voltage | 0.3 | - | V _{CC} - 2 | V |
| I _{FB} | Current Into Feedback Terminal | - | - | 0.3 | mA |
| I _{REF} | Reference Output Current | - | - | 10 | mA |
| CT | Timing Capacitor | 0.00047 | 0.001 | 10 | μF |
| R _T | Timing Resistor | 1.8 | 30 | 500 | kΩ |
| f _{osc} | Oscillator Frequency | 1.0 | 40 | 200 | kHz |
| _ | PWM Input Voltage (Pin 3, 4, 14) | 0.3 | - | 5.3 | V |
| T _A | Operating Free-Air Temperature | -40 | - | +85 | °C |

Electrical Characteristics (T_A=+25°C, V_{CC}=20V, f=10kHz, unless otherwise noted.)

| Symbol | Parameter | Conditions | Min | Тур | Max | Unit |
|-------------------|--------------------------------------|-------------------------------------------------------------------------------|------|------|------|-------|
| ference Sect | ion | | • | | · | |
| | Output Reference Voltage | I _{REF} =1mA | 4.90 | 4.95 | 5.0 | V |
| V_{REF} | for AZ494A | I _{REF} =1mA, T _A = -40 to +85°C | 4.85 | 4.95 | 5.05 | V |
| M | Output Reference Voltage | I _{REF} =1mA | 4.95 | 5.0 | 5.05 | V |
| VDEE | for AZ494C | I_{REF} =1mA, T_{A} = -40 to +85°C | 4.9 | 5.0 | 5.1 | V |
| R _{LINE} | Line Regulation | $V_{CC} = 7V$ to 36V | - | 2 | 25 | mV |
| R _{LOAD} | Load Regulation | I _{REF} =1mA to 10mA | - | 1 | 15 | mV |
| Isc | Short-Circuit Output Current | V _{REF} = 0V | 10 | 35 | 50 | mA |
| cillator Secti | on | | | | | • |
| | | C _T =0.001μF, R _T =30kΩ | - | 40 | _ | |
| fosc | Oscillator Frequency | C _T =0.01μF, R _T =12kΩ | 9.2 | 10 | 10.8 | - kHz |
| 1050 | | C _T =0.01μF, R _T =12kΩ T _A = -40 to +85°C | 9.0 | - | 12 | |
| Δf /ΔT | Frequency Change with Temperature | C _T =0.01μF, R _T =12kΩ T _A = -40 to +85°C | - | _ | 1 | % |





Electrical Characteristics (T_A=+25°C, V_{CC}=20V, f=10kHz unless otherwise noted.) (Cont.)

| Symbol | Parame | ter | Conditions | Min | Тур | Max | Unit |
|--------------------------|------------------------------------|---------------------|----------------------------------------------------------------------------------------|------|------|--------------------|------|
| Dead-Time Cont | trol Section | | | | | | • |
| I _{BIAS} | Input Bias Current | | V_{CC} =15V, V_{PIN4} = 0 to 5.25V | - | -2 | -10 | μΑ |
| D(MAX) | Maximum Duty Cycl | е | V _{CC} =15V, V _{PIN4} = 0V, V _{PIN13} = V _{REF} | 45 | _ | - | % |
| N | | | Zero Duty Cycle | - | 3 | 3.3 | |
| Vith | Input Threshold Volt | age | Maximum Duty Cycle | 0 | - | - | V |
| Error-Amplifier | Section | | | | | | |
| V _{IO} | Input Offset Voltage | | V _{PIN3} = 2.5V | - | 2 | 10 | mV |
| I _{IO} | Input Offset Current | | V _{PIN3} = 2.5V | - | 25 | 250 | nA |
| I _{BIAS} | Input Bias Current | | V _{PIN3} = 2.5V | - | 0.2 | 1 | μΑ |
| V _{CM} | Common-Mode Input Voltage Range | | V _{CC} =7V to 36V | -0.3 | - | V _{CC} -2 | v |
| G _{VO} | Open-Loop Voltage | Gain | V _O =0.5V to 3.5V | 70 | 95 | - | dB |
| BW | Unity-Gain Bandwidth | | - | _ | 650 | - | kHz |
| CMRR | Common-Mode Rejection Ratio | | - | 65 | 80 | - | dB |
| I _{SINK} | Output Sink Current (Feedback) | | $V_{ID} = -15 \text{mV}$ to -5V , $V3 = 0.7 \text{V}$ | -0.3 | -0.7 | - | mA |
| ISOURCE | Output Source Current (Feedback) | | V _{ID} =15mV to 5V, V3 = 3.5V | 2 | - | - | mA |
| PWM Comparat | or Section | | | | | | • |
| VITH | Input Threshold Volt | age | Zero duty cycle | - | 4 | 4.5 | V |
| I _{SINK} | Input Sink Current | | V3 = 0.7V | -0.3 | -0.7 | - | mA |
| Output Section | | | | • | | | · |
| V _{CE} (SAT) | Output Saturation | Common Emitter | V _E = 0V, I _C =200mA | _ | 1.1 | 1.3 | |
| V _{CC} (SAT) | Voltage | Emitter Follower | V _{CC} = 15V, I _E = -200mA | - | 1.5 | 2.5 | V |
| I _C (OFF) | Collector Off-State C | Current | V _{CE} = 36V, V _{CC} =36V | - | 2 | 100 | μΑ |
| I _E (OFF) | Emitter Off-State Cu | rrent | $V_{CC} = V_C = 36V, V_E = 0$ | - | - | -100 | μΑ |
| Total Device | | | | | | - | • |
| Icc | Supply Current | | $V_{PIN6} = V_{REF}, V_{CC} = 15V$ | - | 6 | 10 | mA |
| Output Switchin | ng Characteristics | | | | | | |
| t _R | Rise Time | | Common Emitter Common Collector | _ | 100 | 200 | ns |
| tF | Fall Time | | Common Emitter Common Collector | - | 25 | 100 | ns |





Parameter Measurement Information



Test Circuit









Parameter Measurement Information (Cont.)







Note A: C_L includes probe and jig capacitance.







Note A: CL includes probe and jig capacitance.







Performance Characteristics



Error Amplifier Small-Signal Voltage Gain vs. Frequency



Ordering Information



| Package | Temperature Range | Part Number | Marking ID | Packing |
|---------|-------------------|--------------|------------|------------------|
| SO-16 | | AZ494CMTR-G1 | AZ494CM-G1 | 4000/Tape & Reel |
| PDIP-16 | -40 to +85°C | AZ494AP-G1 | AZ494AP-G1 | 25/Tube |





Marking Information



First Line: Logo and Marking ID (See Ordering Information) Second Line: Date Code Y: Year WW: Work Week of Molding A: Assembly House Code XX: 7th and 8th Digits of Batch No.

SO-16 (Top View)



First Line: Logo and Marking ID (See Ordering Information) Second Line: Date Code Y: Year WW: Work Week of Molding A: Assembly House Code XX: 7th and 8th Digits of Batch No.





Package Outline Dimensions (All dimensions in mm(inch).)

(1) Package Type: SO-16



Note: Eject hole, oriented hole and mold mark is optional.

| Symbol | | [|) | | | D1 | | | |
|---------|---------|---------|-----------|-----------|---------|---------|-----------|-----------|--|
| Cymbol | min(mm) | max(mm) | min(inch) | max(inch) | min(mm) | max(mm) | min(inch) | max(inch) | |
| Option1 | 1.350 | 1.750 | 0.053 | 0.069 | 1.250 | 1.650 | 0.049 | 0.065 | |
| Option2 | - | 1.260 | - | 0.050 | 1.020 | - | 0.040 | - | |





Package Outline Dimensions (All dimensions in mm(inch).) (Cont.)

(2) Package Type: PDIP-16



Note: Eject hole, oriented hole and mold mark is optional.





Suggested Pad Layout

(1) Package Type: SO-16



| Dimensions | Z | G | X | Y | E |
|------------|-------------|-------------|-------------|-------------|-------------|
| | (mm)/(inch) | (mm)/(inch) | (mm)/(inch) | (mm)/(inch) | (mm)/(inch) |
| Value | 6.900/0.272 | 3.900/0.154 | 0.650/0.026 | 1.500/0.059 | 1.270/0.050 |





IMPORTANT NOTICE

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
 - 1. are intended to implant into the body, or
 - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2015, Diodes Incorporated

www.diodes.com