## **SMT Current Sense Transformers**

PA1005.XXXNL Series





Height: 5.5mm Max

Footprint: 8.4mm x 7.2mm Max

Current Rating: up to 20A

Frequency Range: 50kHz to 1MHz

Low Primary DCR version of P820X

Electrical Specifications @ $25^{\circ}$ C — Operating Temperature -40 $^{\circ}$ C to +130 $^{\circ}$ C						
Part <sup>5,6</sup> Number	Turns Ratio	Current <sup>2</sup> Rating (A)	Secondary Inductance (mH MIN)	DCR (mΩ MAX)		Hipot
				Primary (8-7)	Secondary (1-3)	(V <sub>RMS</sub> )
PA1005.020NL	1:20	20	0.08	0.75	550	1000
PA1005.030NL	1:30	20	0.18	0.75	870	1000
PA1005.040NL	1:40	20	0.32	0.75	1140	1000
PA1005.050NL	1:50	20	0.50	0.75	1500	1000
PA1005.060NL	1:60	20	0.72	0.75	2250	1000
PA1005.070NL	1:70	20	0.98	0.75	4750	1000
PA1005.100NL	1:100	20	2.00	0.75	5500	1000
PA1005.125NL	1:125	20	3.00	0.75	6500	500

## NOTES:

- 1. The temperature of component (ambient temperature plus temper-ature rise) must be within the specified operating temperature range.
- 2. The maximum current rating is based upon temperature rise of the component and represents the DC current which will cause a typical temperature rise of 40°C with no airflow when both one turn windings connected in parallel.
- 3. To calculate value of terminating resistor (Rt) use the following formula: Rt  $(\Omega)$  = VREF \* N / (Ipeak\_primary)
- 4. The peak flux density of the device must remain below 2000 Gauss. To calculate the peak flux density for uni-polar current use following formula:

- $Bpk = 37.59 * Vref * (Duty_Cycle_Max) * 10^5 / (N * Freq_kHz)$
- \* for bi-polar current applications divide Bpk (as calculated above) by 2.
- 5. Optional Tape & Reel packaging can be ordered by adding a "T" suffix to the part number (i.e. PA1005.020NL becomes PA1005.020NLT). Pulse complies to industry standard tape and reel specification EIA481.
- 6. The "NL" suffix indicates an RoHS-compliant part number. Non-NL suffixed parts are not necessarily RoHS compliant, but are electrically and mechanically equivalent to NL versions. If a part number does not have the "NL" suffix, but an RoHS compliant version is required, please contact Pulse for availability.

## Mechanical

## **Schematic**

Vref

RT

