

KEY FEATURES

- Electronic instrument enclosures, ideally suited for mounting printed circuit boards.
- Ergonomically designed for a comfortable fit into the user's hand.
- Two piece lap joint construction provides protection against dust accumulation and splashing water.
- Molded in a choice of black or grey general purpose ABS plastic.
- Unit is secured with self-tapping screws.

ACCESSORIES



Replacement Screws Package of 100 self-tapping #4 oval head: **1593KS100** .875" (22.2mm) for K, L & X **1593MS100** .625" (15.9mm) for S & T **1593QS100** .75"" (19.1mm) for J, N, P, Q, D & Y



P.C. Board Screws Self-tapping type, used for bosses in the 1591 lid for P.C. board installation. #4 x 1/4" (6.4 mm) **1593ATS50** - Package of 50 **1593ATS100** - Package of 100



CANADA Guelph, Ontario (519) 822-2960 St. Laurent, Quebec (514) 343-9010 USA Cheektowaga, NY (716) 651-0086





Belt or Pocket Clip Molded from tough nylon, includes 2 nylon screws and mounting template. Black - 1599CLIP Grey - 1599CLIPGY



Optional Infrared Panel Sold in packages of 10 1593DIR10 for 1593D 1593NIR10 for 1593N 1593PIR10 for 1593K, L, P, Q, Y & X 1593SIR10 for 1593S & T

> EUROPE Basingstoke, UK +44 1256 812812



Removable front & rear panels for easy modification (or replace with optional IR panel) - sized to accept most popular connectors...



Part Number		Units	Dimensions			Battery	Front Open	Rear Open
Black	Grey	Units	А	В	С	Compartment	(w/panel)	(w/panel)
1593KBK 15	1593KGY	inch	2.6	2.6	1.1	N	Y	Y
	1593661	mm	66	66	28			
1593LBK	1593LGY	inch	3.6	2.6	1.1	N	Y	Y
1993LDK	1593LG1	mm	92	66	28			
1593NBK		inch	4.3	2.9	1.0	N	V	V
1999INDK 1999INGT	1593NGY	mm	110	75	25	N	ř	r
1593XBK	1593XGY	inch	5.5	2.6	1.1	Ν	Y	v
		mm	140	66	28			ř I

NOTE: 1593N is designed to house the smart card readers.



Optional Infrared Panel Sold in packages of 10 1593NIR10 for 1593N 1593PIR10 for 1593K, L & X



<u>Replacement Screws</u> Package of 100 self-tapping #4 oval head: 1593KS100 .875" (22.2mm) for K, L & X 1593QS100 .75"" (19.1mm) for N



<u>P.C. Board Screws</u> Self-tapping type, used for bosses in the 1591 lid for P.C. board installation. #4 x 1/4" (6.4 mm) **1593ATS50** - Package of 50 **1593ATS100** - Package of 100



<u>CANADA</u> Guelph, Ontario (519) 822-2960 St. Laurent, Quebec (514) 343-9010 <u>USA</u> Cheektowaga, NY (716) 651-0086



EUROPE Basingstoke, UK +44 1256 812812

Recessed top for membrane display or pad...

Plastic





Four P.C. card standoffs molded in both halves...

Part Number		Units	Dimensions			Battery	•	Rear Open
Black	Grey		А	В	С	Compartment	(w/panel)	(w/panel)
1593JBK	1593JGY	inch	2.6	2.6	1.1	N	N	N
		mm	66	66	28	IN	IN	IN

Replacement Screws Package of 100 self-tapping #4 oval head: 1593QS100 .75"" (19.1mm) PCB Screws

To mount P.C. boards into standoffs (#4 x 1/4" pan head screws) 1593ATS100 - Package of 100 1593ATS50 - Package of 50





Part Number		Units	Dimensions			Battery	•	Rear Open
Black	Grey	Units	А	В	С	Compartment	(w/panel)	(w/panel)
1593DBK	1593DGY	inch	4.5	1.4	1.0	N	Y	Y
		mm	114	36	25			

Optional Infrared Panel

1593DIR10 - Package of 10

<u>Replacement Screws</u>

Package of 100 self-tapping #4 oval head: 1593QS100 .75"" (19.1mm) PCB Screws

To mount P.C. boards into standoffs (#4 x 1/4" pan head screws) 1593ATS100 - Package of 100 1593ATS50 - Package of 50



CANADA Guelph, Ontario (519) 822-2960 St. Laurent, Quebec (514) 343-9010 USA Cheektowaga, NY (716) 651-0086



EUROPE Basingstoke, UK +44 1256 812812



Removable front panel (or replace with optional IR panel) for easy modification - sized to accept most popular connectors...

P.C. card standoffs molded in both halves...

Part Number		Units	Dimensions			Battery	Front Open	Rear Open
Black	Grey	Units	А	В	С	Compartment	(w/panel)	(w/panel)
1593SBK	1593SGY	inch	3.6	2.6	.83	Y*	Y	N
19939DK	1593561	mm	92	66	21			
1593PBK 1593PG	1502DCV	inch	3.6	2.6	1.1	Y	Y	Ν
	1595FG1	mm	92	66	28			
1593TBK	1593TGY	inch	4.4	2.6	.83	Y*	Y	N
13931BK	1555161	mm	112	66	21			
1593QBK	1593QGY	inch	4.4	2.6	1.1	Y	×	Ν
1353QDN		mm	112	66	28		1	IN
1593YBK	1593YGY	inch	5.5	2.6	1.1	Y	V	Ν
1393 I DK		mm	140	66	28		Т	IN

NOTES: * Due to their low profile design, the 1593S & 1593T models will not accept batteries larger than AAA.

Battery Holder Kits

- Designed for our battery door enclosures.
- · Kits include all the parts required to install the batteries
- Kit includes the battery holder, wires, divider and foam anti-rattle pad.

Part Number	Battery holder kit for:			
BH1AAWKIT	1 AA Cell			
BH2AAWKIT	2 AA Cells			
BH1AAAWKIT	1 AAA Cell			
BH2AAAWKIT	2 AAA Cells			
BH3AAAWKIT	3 AAA Cells			
BH4AAAWKIT	4 AAA Cells			
BS61KIT	1 - 9V Cell			

Optional Infrared Panel

Package of 10 **1593PIR10** - for 1593P, Q & Y **1593SIR10** - for 1593S & T

<u>Replacement Screws</u>

Package of 100 self-tapping #4 oval head: **1593MS100** .625"" (15.9mm) for 1593S & T **1593QS100** .75"" (19.1mm) for 1593P, Q & Y



PCB Screws

To mount P.C. boards into standoffs (#4 x 1/4" pan head screws) 1593ATS100 - Package of 100 1593ATS50 - Package of 50



CANADA Guelph, Ontario (519) 822-2960 St. Laurent, Quebec (514) 343-9010 USA Cheektowaga, NY (716) 651-0086



EUROPE Basingstoke, UK +44 1256 812812 29