

# STG3384

# Low voltage 0.9Ω max dual SPST switch with break before make feature

### Features

- Low quiescent supply current: Max ± 50µA for V<sub>1IN</sub>, V<sub>2IN</sub> = 1.80V at V<sub>CC</sub> = 4.3V
- Ultra low power dissipation:  $I_{CC} = 0.2\mu A$  (Max) at  $T_A = 85^{\circ}C$ ,  $V_{IN} = 0V$
- Switch: low "ON" resistance:
  - $R_{ON} = 0.7\Omega$  (Max  $T_A = 25^{\circ}C$ ) at  $V_{CC} = 4.3V$
  - $R_{ON} = 0.7\Omega$  (Max  $T_A = 25^{\circ}C$ ) at  $V_{CC} = 3V$
- Wide operating voltage range:
  V<sub>CC</sub> (OPR) = 1.65V to 4.3V single supply
- 4.3V tolerant and 1.8V compatible threshold on digital control input at V<sub>CC</sub> = 1.65 to 4.3V
- Latch-up performance exceeds 300mA (JESD 17)

yosolete Productle

 ESD performance (analog channel vs GND): HBM > 2kV (MIL STD 883 method 3015)



# Description

The STG3384 is a high-speed CMOS low voltage dual analog S.P.S.T. (Single Fole Single Throw) SWITCH fabricated in sili congate C<sup>2</sup>MOS technology. It is designed to operate from 1.65V to 4.3V, making this device ideal for portable.

The nIN inputs are provided to control the switches.

The synches Sn are ON (they are connected to common Ports Dn) when the nIN input is held nigh and OFF (high impedance state exists between the two ports) when nIN is held low.

Additional key features are fast switching speed, and Ultra Low Power Consumption. All inputs and outputs are equipped with protection circuits against static discharge, giving them ESD immunity and transient excess voltage.

### Order codes

Part number	Package	Packaging
STG3384DTR	TDFN10 (2.5mm x 1.3mm)	Tape and reel

August 2006

# Contents

1	Devi	ce description
	1.1	I/O equivalent circuit
	1.2	Truth table
2	Pin	settings
	2.1	Pin connection
	2.2	Pin description
3	Мах	imum rating
	3.1	Recommended operating conditions
4	Elec	trical characteristics6
	4.1	DC electrical characteristics 6
	4.2	AC electrical characteristics
	4.3	Analog switch characteristics
5	Pack	kage mechanical data
6	Revi	sion history
0050	ete	producils



#### **Device description** 1

#### I/O equivalent circuit 1.1

### Figure 1. Input and output equivalent circuit



#### 1.2 **Truth table**

### Table 1. Truth table

nIN	Switch Sn
Н	ON
L	OFF <sup>(1)</sup>
1. High impedance	5)
obsolete Productl	



#### **Pin settings** 2

#### **Pin connection** 2.1

#### Figure 2. Pin connection (top through view)



#### 2.2 **Pin description**

### Table 2. Pin description

	Pin N°	Symbol	Name and function
	5, 10	1IN, 2IN	Controls
	2, 9	S1, S2	Independent channels
	3, 8	D1, D2	Common channels
	1	V <sub>cc</sub>	Possitive supply voltage
	6	GND	Ground (0V)
	4, 7	NC	Not connected
0105018	teprous		



# 3 Maximum rating

stressing the device above the rating listed in the "absolute maximum ratings" table may cause permanent damage to the device. these are stress ratings only and operation of the device at these or any other conditions above those indicated in the operating sections of this specification is not implied. exposure to absolute maximum rating conditions for extended periods may affect device reliability. refer also to the STMicroelectronics sure program and other relevant quality documents.

Symbol	Parameter	Value	Unit
$V_{CC}$	Supply voltage	-0.5 to 5.5	V
VI	DC input voltage	-0.5 to V <sub>CC</sub> + 0.5	V
$V_{IC}$	DC control input voltage	-0.5 to 5.5	V
V <sub>O</sub>	DC output voltage	-0.5 to V <sub>CC</sub> + 0.5	V
I <sub>IKC</sub>	DC Input diode current on control pin (V <sub>IN</sub> < 0V)	-50	mA
Ι <sub>ΙΚ</sub>	DC input diode current (V <sub>IN</sub> < 0V)	±50	mA
I <sub>ОК</sub>	DC output diode current	±20	mA
Ι <sub>Ο</sub>	DC output current	±200	mA
I <sub>OP</sub>	DC output current peak (pulse at 1ms, 10% duty cycle)	±400	mA
I <sub>CC</sub> or I <sub>GND</sub>	DC V <sub>CC</sub> or ground current	±100	mA
PD	Power dissipation at $T_A = 70^{\circ}C^{(1)}$	1120	mW
T <sub>stg</sub>	Storage temperature	-65 to 150	°C
ΤL	Lead temperature (10 sec)	300	°C

1. Derate above 70C by 18.5mW/C

# 3.1 Recommended operating conditions

#### Table 4. Recommended operating conditions

	necommended operating condi-			
Symbo	I Parameter	Value	Unit	
V <sub>CC</sub>	Supply voltage (1)		1.4 to 4.3	V
VI	Input voltage		0 to V <sub>CC</sub>	V
V <sub>IC</sub>	Control input voltage	0 to 4.3	V	
Vo	Output voltage		0 to V <sub>CC</sub>	V
T <sub>op</sub>	Operating temperature		-55 to 125	°C
dt/dv	Input rise and fall time control input	$V_{CC} = 1.65V \text{ to } 2.7V$	0 to 20	ns/V
ul/uv		V <sub>CC</sub> = 3.0 to 4.3V	0 to 10	115/ V

1. Truth table guaranteed: 1.5V to 3.6V



# 4 Electrical characteristics

## 4.1 DC electrical characteristics

### Table 5. DC specifications

		Test co	nditions	Value							
Symbol	Parameter			TA	= 25°C	;	-40 to 8	35°C	-55 to 12	25°C	Unit
		Vcc (V)		Min	Тур	Max	Min	Max	Min	Max	
		1.65-1.95		$0.65V_{CC}$			$0.65V_{CC}$		$0.65V_{CC}$		
V <sub>IH</sub>	High level	2.3-2.5		1.4			1.4		1.4		v
۷IH	input voltage	2.7-3.0		1.4			1.4		1.4		v
		3.3 – 4.3		1.5			1.5		1.5		
		1.65-1.95				0.40		0.40		0.40	
V	Low level	2.3-2.5				0.50		0.50		0.50	
$V_{IL}$	input voltage	2.7-3.0		-		0.50		0.50	. C	0.50	V
		3.3 – 4.3				0.50		0.50	<u> </u>	0.50	
		4.3			0.5	0.7	0	1.4			
		3.0			0.7	0.9	X	1.4			
Б	Switch ON resistance	2.7	$V_{\rm S} = 0V$ to $V_{\rm CC}$ $I_{\rm S} = 100 {\rm mA}$		0.7	0.9	6	1.7			
R <sub>ON</sub>		2.3			0.9	1.2		1.7			Ω
		1.8		N	1.3	1.6		1.9			
		1.65		0	1.6	2.5		2.2			
ΔR <sub>ON</sub>	ON resistance match between channels Sn	2.7	V <sub>S</sub> @ R <sub>ON</sub> Max I <sub>S</sub> =100mA		0.6						Ω
		4.3			0.18	0.21					
	ON	3.0	V <sub>S</sub> = 0V to		0.16	0.19					
R <sub>FLAT</sub>	resistance flatness	2.7	V <sub>CC</sub>	-	0.16	0.19					Ω
6	(1) (2)	2.3	I <sub>S</sub> =100mA		0.18	0.21					
07		1.65			0.38	0.44					
I <sub>OFF</sub>	OFF state leakage current (Sn), (Dn)	4.3	V <sub>S</sub> = 0.3 or 4V			±10		±100			nA

		Test conditions		Value							
Symbol	Parameter			Τ <sub>Α</sub>	= 25°(	0	-40 to 8	35°C	-55 to 1	25°C	Unit
		Vcc (V)		Min	Тур	Max	Min	Max	Min	Max	
I <sub>IN</sub>	Input leakage current	0-4.3	V <sub>IN</sub> = 0 to 4.3V			±0.1		±1			μΑ
I <sub>CC</sub>	Quiescent supply current	1.65 – 4.3	V <sub>IN</sub> = V <sub>CC</sub> or GND			±0.05		±0.2		±1	μΑ
loow	Quiescent supply current low	4.3	V <sub>1IN</sub> , V <sub>2IN</sub> = 1.65V		42	55					
ICCLV	voltage driving	4.0	V <sub>1IN</sub> , V <sub>2IN</sub> = 1.80V		38	50					μA

#### Table 5. DC specifications

1.  $\Delta R_{ON} = R_{ON(MAX)} - R_{ON(MIN)}$ .

. dreame bootsolete bo 2. Flatness is defined as the difference between the maximum and minimum value of on-resistance as measured over the specified analog signal ranges.

57

# 4.2 AC electrical characteristics

 $C_L$  = 35pF,  $R_L$  = 50 $\Omega$ ,  $t_r$  =  $t_f \leq$ 5ns

### Table 6. AC specifications

		Test con	Value								
Symbol	Parameter	Vcc		T <sub>A</sub> = 25°C		-40 to	85°C	-55 to	125°C	Ur	
		(V)		Min	Тур	Max	Min	Мах	Min	Max	
		1.65-1.95			0.45						
t t	Propagation delay	2.3-2.7			0.40						
'PLH', 'PHL	Propagation delay	3.0-3.3			0.30						n
		3.6-4.3			0.30						
		1.65-1.95	$V_{\rm S} = 0.8 V$		70						
tou	Turn-ON time	2.3-2.7			30	60		75			
t <sub>ON</sub>	ium-on time	3.0-3.3	V <sub>S</sub> = 1.5V		25	50		60		15	n
		3.6-4.3			25	50		60	۰.C	11	
		1.65-1.95	V <sub>S</sub> = 0.8		45			6	0		
+.	Turn-OFF time	2.3-2.7			25	30	~	40			
t <sub>OFF</sub>		3.0-3.3	V <sub>S</sub> = 1.5V		25	30	Y	40			ns
		3.6-4.3			25	30	1	40			
		1.65 – 1.95				0					
t_	Break before	2.3 – 2.7	$C_L = 35pF$ $R_L = 50\Omega$	2	15						_
t <sub>D</sub>	make time delay	3.0 - 3.6	V <sub>S</sub> = 1.5V	2	15						r
		3.6 – 4.3		2	15						
		1.65-1.95	C <sub>I</sub> =100pF		23						
Q	Charge Injection	2.3-2.7	$R_L=1M\Omega$		32						p
Q		3.0-3.3	V <sub>GEN</sub> =0V		40						β
		3.6-4.3	R <sub>GEN</sub> =0Ω		44						



# 4.3 Analog switch characteristics

 $C_L = 5pF$ ,  $R_L = 50\Omega$ ,  $T_A = 25^{\circ}C$ 

#### Table 7. Analog switch characteristics

			Test conditions			Value						
Symbol	Parameter	Vcc		T <sub>A</sub> = 25°C -40 to 85°					5°C -55 to 125°C			
		(V)		Min	Тур	Max	Min	Max	Min	Max		
OIRR	OFF Isolation (1)	1.65-4.3	V <sub>S</sub> = 1V <sub>RMS</sub> f = 100kHz		-90						dB	
Xtalk	Crosstalk	1.6-4.3	V <sub>S</sub> = 1V <sub>RMS</sub> f = 100kHz		-76						dB	
THD	Total Harmonic Distortion	3.0	$R_{L} = 600\Omega$ $V_{IN} = 2V_{PP}$ $f = 20Hz \text{ to } 20$ $kHz$		0.03						%	
BW	-3dB bandwidth	1.65-4.3	R <sub>L</sub> = 50Ω		85						MHz	
C <sub>IN</sub>	Control pin input capacitance				5				30			
C <sub>Sn</sub>	Sn port capacitance	3.3	f = 1MHz		20		2	$(\mathbf{O})$			pF	
C <sub>D</sub>	D port capacitance when switch is enabled	3.3	f = 1MHz		70	ete	5					

1. OFF Isolation =  $20Log_{10}$  (V<sub>D</sub>/V<sub>S</sub>), V<sub>D</sub> = output, V<sub>S</sub> = input at off switch

57

# 5 Package mechanical data

In order to meet environmental requirements, ST offers these devices in ECOPACK® packages. These packages have a Lead-free second level interconnect. The category of second level interconnect is marked on the package and on the inner box label, in compliance with JEDEC Standard JESD97. The maximum ratings related to soldering conditions are also marked on the inner box label. ECOPACK is an ST trademark. ECOPACK specifications are available at: www.st.com

	DFN10 (2.5x1.3) MECHANICAL DATA											
DIM	DIM. mils											
DIM.	MIN.	ТҮР	MAX.	MIN.	TYP.	MAX.						
A	0.50	0.55	0.60	19.7	21.7	23.6						
A1	0	0.02	0.05	0	0.8	2.0						
b	0.18	0.23	0.30	7.1	9.1	11.8						
D	2.40	2.50	2.60	94.5	98.4	102.4						
E	1.30	1.40	1.50	51.2	55.1	59.1						
е		0.50			19.7							
к	0.20			7.9								
L	0.45	0.50	0.55	17.7	19.7	21.6						
L1			0.15			5.9						



57

# 6 Revision history

### Table 8. Revision history

Date	Revision	Changes
02-Aug-2006	1	First release

obsolete Product(s). Obsolete Product(s)



#### Please Read Carefully:

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.

UNLESS EXPRESSLY APPROVED IN WRITING BY AN AUTHORIZED ST REPRESENTATIVE, ST PRODUCTS ARE NOT RECOMMENDED, AUTHORIZED OR WARRANTED FOR USE IN MILITARY, AIR CRAFT, SPACE, LIFE SAVING, OR LIFE SUSTAINING APPLICATIONS, NOR IN PRODUCTS OR SYSTEMS WHERE FAILURE OR MALFUNCTION MAY RESULT IN PERSONAL INJURY, DEATH, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE. ST PRODUCTS WHICH ARE NOT SPECIFIED AS "AUTOMOTIVE GRADE" MAY ONLY BE USED IN AUTOMOTIVE APPLICATIONS AT USER'S OWN RISK.

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2006 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan -Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

